

Lithium Battery

51.2V 300AH 15.36KWH

· Safety and Intelligent

Long life LiFePO4 cells, high energy density, build in BMS and passive protection

Easy to Install and Use

Modular design, simple operation

· Long Life Span

10 years design life, more than 6000cycles

Adaptable to Harsh Environment Adapt to wide range of temperature and humidity

· Support Bluetooth/WIFI function

(optional)

Can be controlled remotely to reduce operation and maintenance costs

· Multi-scenario application

Household use, small industrial and commercial applications



Lithium Battery

Technical Parameters

| Nominal voltage | 51.2V |
|------------------------------|--|
| Nominal capacity | 300Ah |
| Energy | 15.36kwh |
| Interal Resistance | ≤200mΩ |
| Cycle Life | >6000 cycles @ 0.2C 80%D.O.D |
| Months Self Discharge | <3% |
| Efficiency of Charge | 99.5%@ 0.20 |
| Effciency of Discharge | 96-99%@ 10 |
| Charge Voltage | 58.4±0.5V |
| Charge Mode | cc/cv |
| Charger Current | 40A |
| Max Charge Current | 200A |
| Charge Cut-off Voltage | 58.4 |
| Continuous discharge Current | 40A |
| max discharge Current | 200A |
| Discharge Cut-off Voltage | 43.2V |
| Charge Temperature | 0 ℃ to 45 ℃ |
| Discharge Temperature | -20 ℃ to 55 ℃ |
| Storage Temperature | -10 °C to 40 °C |
| Water Dust Resistance | IP20 |
| Cell & Method | EVE 3.2V304Ah-16S1 |
| Terminal | 200A |
| Protocol (optional) | RS232/RS485/CAN/BLUETOOTH/WIFI |
| BMS | 200A |
| Safety & Certification | CELL:UL1642/UL1973/IEC62619/CE/CB/UN38.3/UL9540/ROHS/REACH |
| Size (mm) | 772*460*237(D*W*H) |
| Net weight (kg) | 114KG |
| Wooden box package size (mm) | 940*555*405 |
| Quantity of loading | 120pcs/20ft 240pcs/40ft |

Notes

Compatibility Inverters





















^{*1} Test conditions: Based on the factory date, charge and discharge rate at 0.2C at 100% discharge depth (DoD) and 25

^{*2} The weight of the battery module is based on the actual product, with a tolerance of ± 3% allowed

^{*3} The installation of battery packs is related to product quality assurance, safe and stable operation. Please follow the requirements of the user manual for standardized installation, use, and routine maintenance